

# POSITIVE SWITCHING (NORMAL BUS)

| BUSF200 |              | XLM              |       | COMMENT  |
|---------|--------------|------------------|-------|--|
| PIN     | WIRE         | PL1<br>SPADE CON | PL2   |  |
| 1       | BROWN        | 6 +(-)           | 8 LH  | N/C  |
| 2       | N/C          |                  |       | N/C  |
| 3       | ORANGE       |                  |       | TO L/H AMBER LIGHT   |
| 4       | N/C          |                  |       |  |
| 5       | GREEN        |                  | 1 RH  | TO R/H AMBER LIGHT   |
| 6       | BLUE         |                  | 4 SWL | DOOR SWITCH GND SWITCHING                                  |
| 7       | VOILET       |                  |       | N/C  |
| 8       | GREY         |                  | 7 IND | POWER FOR AMBER AND HEADLIGHTS<br>TO XLM DASH SWITCH PIN 3 |
| 9       | WHITE        | 4 RHO            | 5 SWH | DOOR SWITCH + SWITCHING                                    |
| 10      | BLACK        |                  | 2 +V  | XLM SWITCH PIN 1   |
| 11      | BROWN/WHITE  |                  |       | TO R/H HEADLIGHT   |
| 12      | RED/WHITE    |                  | 3 NEG |  |
| 13      | ORANGE/WHITE |                  |       | TO L/H HEADLIGHT   |
| 14      | YELLOW/WHITE |                  |       | HIGH BEAM IN   |
| 15      | GREEN/WHITE  |                  |       | HIGH BEAM OUT  |
| 16      | BLUE/WHITE   |                  |       | LOW BEAM POWER (LINK 8 & 5 TOGETHER)                       |
|         |              | 1 LHO            |       |  |
|         |              | 7 HBI            |       |  |
|         |              | 2 HBO            |       |  |
|         |              | 8 LHI, 5 RHI     |       |  |

PROVISIONAL ONLY REFER ALSO TO XLM BLOCK WIRING DIAGRAM

NOTE: BUSF200 MODULE IS PROPRIETARY TO REDARC ELECTRONICS

GYROSS PTY LTD  
DATE: 26/02/2021  
REDARC BUSF200 to XLM WIRING TABLE